

**CONTROL DEVICE AND SWITCHING UUK-12-02, UUK-24-02****Description**

Control device and switching UUK designed to control connecting and disconnecting of the devices included in the systems of the guard-fire signaling, and switching of actuators (lamps, sirens, video cameras, fire suppression systems, electromagnetic locks, etc.) to the AC mains with a nominal voltage of 220 V or the DC power source 30V by closing or opening the relay contacts

**Electrical characteristics**

Switching current	≤8 A
Switching AC voltage	≤250 V (power ≥2kW)
Switching DA voltage	≤ 30 V (power ≥240W)
Rated voltage on the device control coil	12 V ± 10%, 24 V ± 10%
Current of the control relay coil of the device is no more than	55mA
Overall dimensions of the UUK device no more than	85x62x42 mm
Weight of the device is not more than	120 g
Operating temperature	-30...+50°C

Type of performance	Number of executive relays	Voltage on the control coil	Type of terminal, cross-section of connecting cable
UUK-12-02	2	12 V	DG3 to 1,5mm ²
UUK-24-02	2	24 V	DG3 to 1,5mm ²